



DIGITRADIO 380 CD IR

DAB+/FM/Internet stereo radio with CD player, Bluetooth, Spotify Connect and control via app

| EAN | Colour | Item no. | Weight (Box) | Weight | Device (W x H x D) | Box |
|---------------|--------|-----------|--------------|---------|--------------------------|--------------------------|
| 4019588039544 | black | 0000/3954 | 6.37 kg | 4.55 kg | 45.00 x 13.80 x 25.40 cm | 51.50 x 19.20 x 33.50 cm |
| 4019588139541 | silver | 0001/3954 | 6.37 kg | 4.55 kg | 45.00 x 13.80 x 25.40 cm | 51.50 x 19.20 x 33.50 cm |

TOP FEATURES

DAB+ digital radio

FM radio (with RDS and PLL)

Limitless music variety via Internet radio

Audio streaming (Spotif, Bluetooth)

TFT colour display (2.4")

Favourites memory (20 for DAB+ and 20 for FM)

CD player with MP3 playback

USB interface with charging function and mp3 playback

Control via the TechniSat CONNECT app (iOS, Android)

WLAN

WLAN : 802.11 a / b / g / n (2.4 GHz and 5 GHz band supported)

AMBIENT OPERATING CONDITIONS

Humidity : 5 - 90 % relative air humidity (non-condensing)

Ambient temperature : 5 - 35 °C

BLUETOOTH VERSION & PROFILE

Bluetooth version : 4.2

AVRCP (Audio Video Remote Control Profile) : Yes

A2DP (Advanced Audio Distribution Profile) : Yes

CONNECTIONS

USB : 1

Audio in/AUX in : Yes

Headphone connection jack (3,5mm) : 1

DISPLAY

Size : 2.4 in

Slide show/catSLS : Yes

RadioVIS : Yes

Type : TFT colour display

Dimmable : Yes

FUNCTIONS

MP3 playback via USB : Yes

USB charging function : Yes

CD player with MP3 : Yes

HANDLING/COMFORT

Clock : Yes

Alarm : Yes

Sleep timer : Yes

Snooze : Yes

Remote control : Yes

CONNECT app : Yes

Favourites programme manager DAB+ : 20

Favourites programme manager FM : 20

LOUDSPEAKERS

Stereo speakers : Yes

Output performance : 40 W (RMS)

Stereo : 2 x 20 W

Equalizer : Yes

NETWORK & COMMUNICATION

Bluetooth : Yes

OTHER FEATURES

OSD languages : English, German, French, Polish, Italian, Dutch, Czech, Norwegian, Danish, Spanish, Portuguese, Slovenian, Turkish

POWER CONSUMPTION

Power consumption in standby mode with active network connection : 0,9 W

In operation : 60 W

Standby : 0,9 W

Off status : 0 W

POWER SUPPLY

Nominal voltage : 230 V

Frequency : 50 Hz

Type of power supply : Internal

RADIO / RECEPTION

DAB+ : 174 - 240 MHz

FM/RDS : 87.5 - 108 MHz

Internet radio : Yes

Aerial : DAB / FM telescopic antenna

RADIO TYPE

stationary radio : Yes

STREAMING

Bluetooth audio streaming : Yes

Spotify Free : Yes

SCOPE OF DELIVERY

DIGITRADIO 380 CD IR, remote control,
instruction manual